868.35 MHZ SAW FILTER

- Designed to Provide Front-end Selectivity in 868.35 MHz
- Low-Loss, Coupled-Resonator Quartz Design
- Simple External Impedance Matching
- Ultra Miniature Ceramic QCC8C SMD Package
- Complies with Directive 2002/95/EC (RoHS Compliant)

SF5904

VANLONG

| ABSOLUTE MAXIMUM RATING ($T_A=25^{\circ}$ C) | | | | | |
|---|-----------------|-----------|------|--|--|
| Parameter | | Rating | Unit | | |
| Input Power Level | P_{in} | 10 | dBm | | |
| DC Voltage VDC Between Any Two Pins | V _{DC} | 12 | V | | |
| Operating Temperature Range | T _A | -10 ~ +60 | °C | | |
| Storage Temperature Range | $T_{ m stg}$ | -40 ~ +85 | °C | | |

| ELECTRONIC CHARACTERISTICS | | | | | | |
|---|--------------------------------------|-----------------|---------|----------------|---------|--------------------|
| Parameter | | Sym | Minimum | Typical | Maximum | Unit |
| Nominal Frequency (at 25°C) (Center frequency between 3dB point) | | f _C | NS | 868.35 | NS | MHz |
| Insertion Loss Attenuation | | IL | - | 3.5 | 5.5 | dB |
| 3dB Passband | | BW ₃ | - | 1.2 | - | MHz |
| Passband Ripple | | - | - | - | ±1.0 | dB |
| Rejection | At f _C - 21.4 MHz (Image) | - | 30 | 42 | - | dB |
| | At f _C - 10.7 MHz (LO) | - | 20 | 35 | - | dB |
| | Ultimate | - | - | 60 | - | dB |
| Temperature Stability | Operating Temperature Range | Tc | -10 | - | +60 | °C |
| | Turnover Temperature | To | 25 | - | 55 | °C |
| | Turnover Frequency | f _O | - | f _C | - | MHz |
| | Frequency Temperature Coefficient | FTC | - | 0.032 | - | ppm/C ² |
| Frequency Aging Absolute Value during the First Year | | fA | - | - | 10 | ppm/yr |
| DC Insulation Resistance Between any Two Pins | | - | 1.0 | - | - | MΩ |

NS = Not Specified

Notes:

- 1. The frequency $f_{\rm C}$ is defined as the midpoint between the 3dB frequencies.
- 2. Unless noted otherwise, all measurements are made with the filter installed in the specified test fixture that is connected to a 50Ω test system with VSWR \leq 1.2:1. The test fixture L and C are adjusted for minimum insertion loss at the filter center frequency, f_C . Note that insertion loss, bandwidth, and passband shape are dependent on the impedance matching component values and quality.
- 3. Unless noted otherwise, specifications apply over the entire specified operating temperature range.
- 4. Frequency aging is the change in f_c with time and is specified at +65°C or less. Aging may exceed the specification for prolonged temperatures above +65°C. Typically, aging is greatest the first year after manufacture, decreasing in subsequent years.


- 5. Turnover temperature, T_0 , is the temperature of maximum (or turnover) frequency, f_0 . The nominal frequency at any case temperature, T_c , may be calculated from: $f = f_0 [1 FTC (T_0 T_c)^2]$.
- 6. The specifications of this device are based on the test circuit shown above and subject to change or obsolescence without notice.
- All equipment designs utilizing this product must be approved by the appropriate government agency prior to manufacture or sale.
- Our liability is only assumed for the Surface Acoustic Wave (SAW) component(s) per se, not for applications, processes and circuits implemented within components or assemblies.
- For questions on technology, prices and delivery please contact our sales offices or e-mail sales@vanlong.com.


| Phone: +86 (10) 5820-3910 | Fax: +86 (10) 5820-3915 |
|--------------------------------|-------------------------|
| SF5904 | Revision #1 |
| © VANLONG TECHNOLOGY CO., LTD. | August 02, 2010 |

868.35 MHZ SAW FILTER



PACKAGE DIMENSIONS (QCC8C)





Electrical Connections

| Terminals | Connection | |
|-----------|----------------|--|
| 1 | Input | |
| 2 | Input Ground | |
| 5 | Output | |
| 6 | Output Groud | |
| 3,7 | To be Grounded | |
| 4,8 | Case Ground | |

Package Dimensions

| Dimensions | Nom (mm) | Dimensions | Nom (mm) | |
|------------|----------|------------|----------|--|
| A | 2.08 | E | 1.20 | |
| В | 0.60 | F | 1.35 | |
| С | 1.27 | G | 5.00 | |
| D | 2.54 | Н | 5.00 | |




MARKING

SF5904 YWW

- Laser or Ink marking.
 SF5904 Part Code
 Date Code:
 - Y : Last digit of year WW : Week No.

TEST CIRCUIT



C = 4 ~6 pF Ls1 = Ls2 = 2 turns of 0.5mm insulated copper, 3.0mm ID

TYPICAL FREQUENCY RESPONSE

▶1: Transmission /M Log Mag 10.0 dB/ Ref -4.00 dB ▶2: Transmission /M Log Mag -4.00 dB 1.Ø dB/ Ref dB Ch1D 2 1 Ø N -1 -2 - 3 Ch2 -5 Abs Span 80.000 MHz Span 5.000 MHz Center 868.350 MHz Center 868.350 MHz

Phone: +86 (10) 5820-3910 SF5904 Fax: +86 (10) 5820-3915

Email: sales@vanlong.com